### **DATASHEET - DILM12-XP1**



### Paralleling link, for DILM7-12/MP20

Part no. DILM12-XP1
Catalog No. 281193
Eaton Catalog No. XTCEXPLKB
EL-Nummer 0004110350

(Norway)



### **Delivery program**

Contact sequence	<u></u>
Product range	Accessories
Accessories	Wiring accessories
For use with	DILM7 - DILM15 DILMP20
For use with	Paralleling links for DILM7 to DILM15 Paralleling links for DILMP20
Instructions AC1 current carrying capacity of the open contactor increases by a factor of 2.5 Protected against accidental contact in accordance to VDE 0106 part 100 4th pole can be broken off	

## **Technical data**

#### **Parallel link**

Terminal capacities		$\text{mm}^2$	
Solid		$mm^2$	1 - 16
Flexible with ferrule		$\text{mm}^2$	1 x (0.5 - 25) 2 x (0.5 - 16)
Stranded		mm <sup>2</sup>	1 x (0.5 - 25) 2 x (0.5 - 16)
Flat conductor	Lamellenzahl x Breite x Dicke	mm	6 x 9 x 0.8
Tightening torque		Nm	4
Tool			
Pozidriv screwdriver		Size	2
Conventional thermal current	$\mathbf{I}_{th} = \mathbf{I}_{e}$	Α	
3 pole	I <sub>th</sub>	Α	50

# Design verification as per IEC/EN 61439

In	Α	50
P <sub>vid</sub>	W	0.2
P <sub>vid</sub>	W	0.2
$P_{vs}$	W	0
P <sub>diss</sub>	W	0
	°C	-25
	°C	60
		Meets the product standard's requirements.
		Meets the product standard's requirements.
		Meets the product standard's requirements.
		Meets the product standard's requirements.
	P <sub>vid</sub> P <sub>vid</sub> P <sub>vs</sub> P <sub>diss</sub>	P <sub>vid</sub> W P <sub>vid</sub> W P <sub>vs</sub> W P <sub>diss</sub> W °C °C

10.2.4 Resistance to ultra-violet (UV) radiation	Meets the product standard's requirements.
10.2.5 Lifting	Does not apply, since the entire switchgear needs to be evaluated.
10.2.6 Mechanical impact	11.7
,	Does not apply, since the entire switchgear needs to be evaluated.
10.2.7 Inscriptions	Meets the product standard's requirements.
10.3 Degree of protection of ASSEMBLIES	Does not apply, since the entire switchgear needs to be evaluated.
10.4 Clearances and creepage distances	Meets the product standard's requirements.
10.5 Protection against electric shock	Does not apply, since the entire switchgear needs to be evaluated.
10.6 Incorporation of switching devices and components	Does not apply, since the entire switchgear needs to be evaluated.
10.7 Internal electrical circuits and connections	Is the panel builder's responsibility.
10.8 Connections for external conductors	Is the panel builder's responsibility.
10.9 Insulation properties	
10.9.2 Power-frequency electric strength	Is the panel builder's responsibility.
10.9.3 Impulse withstand voltage	Is the panel builder's responsibility.
10.9.4 Testing of enclosures made of insulating material	Is the panel builder's responsibility.
10.10 Temperature rise	The panel builder is responsible for the temperature rise calculation. Eaton will provide heat dissipation data for the devices.
10.11 Short-circuit rating	Is the panel builder's responsibility. The specifications for the switchgear must be observed.
10.12 Electromagnetic compatibility	Is the panel builder's responsibility. The specifications for the switchgear must be observed.
10.13 Mechanical function	The device meets the requirements, provided the information in the instruction leaflet (IL) is observed.

### **Technical data ETIM 7.0**

Low-voltage industrial components (EG000017) / Accessories for low-voltage switch technology (EC002498)

Electric engineering, automation, process control engineering / Low-voltage switch technology / Component for low-voltage switching technology / Component for low-voltage switch technology (accessories) (ecl@ss10.0.1-27-37-13-92 [AKN570013])

Type of accessory Connecting bridge

## **Approvals**

Product Standards	IEC/EN 60947-4-1; UL 508; CSA-C22.2 No. 14-05; CE marking
UL File No.	E29096
UL Category Control No.	NLDX
CSA File No.	012528
CSA Class No.	3211-03
North America Certification	UL listed, CSA certified
Specially designed for North America	No

## **Additional product information (links)**

-		
IL03406009Z (AWA2100-1737) Accessories for Contactors > 170 A		
IL03406009Z (AWA2100-1737) Accessories for Contactors > 170 A	ftp://ftp.moeller.net/DOCUMENTATION/AWA_INSTRUCTIONS/IL03406009Z2018_06.pdf	
Motor starters and "Special Purpose Ratings" for the North American market	http://www.eaton.eu/ecm/groups/public/@pub/@europe/@electrical/documents/content/pct_3258146.pdf	
Switchgear of Power Factor Correction Systems	http://www.moeller.net/binary/ver_techpapers/ver934en.pdf	
X-Start - Modern Switching Installations Efficiently Fitted and Wired Securely	http://www.moeller.net/binary/ver_techpapers/ver938en.pdf	
Mirror Contacts for Highly-Reliable Information Relating to Safety-Related Control Functions	http://www.moeller.net/binary/ver_techpapers/ver944en.pdf	
Effect of the Cabel Capacitance of Long Control Cables on the Actuation of Contactors	http://www.moeller.net/binary/ver_techpapers/ver949en.pdf	
Switchgear for Luminaires	http://www.moeller.net/binary/ver_techpapers/ver955en.pdf	
Standard Compliant and Functionally Safe Engineering Design with Mechanical Auxiliary Contacts	http://www.moeller.net/binary/ver_techpapers/ver956en.pdf	
The Interaction of Contactors with PLCs	http://www.moeller.net/binary/ver_techpapers/ver957en.pdf	
Busbar Component Adapters for modern Industrial control panels	http://www.moeller.net/binary/ver_techpapers/ver960en.pdf	